



## PRODUCT TECHNICAL SHEET

30 June 2024

### MXM 06

#### 6 CH Microphone Mixer

Compact audio mixer with 6 channels for simultaneous mixing of 4 balanced signals (line or mic), 1 channel via RCA (line) and 1 digital signal (mp3 or bluetooth player). It comes with graphic 7-band equalizer and echo effect that can be applied to microphones. The first 4 channels can also manage (through XLR) condenser microphones, thanks to phantom power supply. The USB socket allows the connection to PCs to use the mixer as if it were an audio card.. It is powered by an external transformer included in the package.

<b>Input connectors</b>	XLR + RCA + Jack 6,3mm
<b>Output connectors</b>	6,3mm jack
<b>Line inputs</b>	6
<b>Mic inputs</b>	4
<b>Number of channels</b>	6
<b>Graphic equalizer</b>	Yes
<b>Echo function</b>	Present
<b>Effects</b>	send / return for external effects
<b>Phantom Key</b>	Yes, it allows to enable phantom power for condenser microphones
<b>VU METERS</b>	Yes
<b>Pre-listening</b>	No
<b>Frequency response</b>	10 Hz - 60 KHz (+/-3dB)
<b>Voice priority function</b>	No
<b>Color</b>	Grey and black
<b>Weight</b>	1,2
<b>Product dimensions</b>	260 x 190 x 55 mm
<b>Power supply</b>	15V DC through adaptor
<b>Notes</b>	bluetooth and sound card mode



Puoi trovare articoli correlati, accessori ed aggiornamenti su:

[www.karmaitaliana.it](http://www.karmaitaliana.it)

**Inoltre potrai scaricare i nostri cataloghi in formato PDF per:**

- DeeJay - Mixer & Disco Light - Microfoni e raddiomicrofoni - Alimentatori / accessori - Staffe porta TV - Amplificazione stereo - Diffusori passivi / amplificati - Sicurezza



8015439320065