

# KARMA®

— GLEMM — rídem —

SCHEDA TECNICA / TECHNICAL SHEET

## PAA 480MZ

6 zone 480W amplifier



Complete and performant PA amplifier. It can manage up to 480W of power distributed over 6 zones, each of them with independent volume control. It is possible to connect up to 6 input signals (1 mic + 3 line/mic + 2 line). Three of the four mic inputs support phantom power supply. The volume controls on the front panel are quick and practical to use. Thanks to a sophisticated multimedia module it is possible to play Mp3 tracks (via SD or USB), listen to radio stations and connect to bluetooth devices.

<b>MP3 compatible</b>	Yes
<b>Input connectors</b>	XLR + jack 6,3mm
<b>Output connectors</b>	Terminals
<b>Rack space</b>	2U
<b>Line inputs</b>	6 (1 mic + 3 line/mic + 2 line)
<b>Mic inputs</b>	4 (3 x XLR with phantom + 1 x 6,3mm jack)
<b>CD/ USB</b>	USB and SD
<b>Impedance</b>	4 - 8 - 16 Ohms
<b>Constant voltage</b>	70 - 100V compatible
<b>Multi zone</b>	6 zones, each with independent volume
<b>Frequency response</b>	80Hz- 16KHz
<b>VU METERS</b>	Yes
<b>Phantom Key</b>	Yes
<b>RMS power</b>	240W
<b>Mp3 player</b>	Yes
<b>Matrix</b>	No
<b>Max power</b>	480W
<b>DC Power</b>	24V
<b>Bluetooth</b>	Ver. 5.0
<b>Color</b>	black
<b>Weight</b>	10 kg
<b>Product dimensions</b>	484 x 88 x 405
<b>Power supply</b>	220V

DOWNLOAD 

Scarica ora  
il catalogo aggiornato



SCOPRI TUTTE LE NOVITÀ  
SUL NOSTRO SITO

[www.karmaitaliana.it](http://www.karmaitaliana.it)



8015439104801

Karma Italiana srl si impegna affinché le informazioni contenute in questa scheda siano le più precise possibili. Allo scopo di migliorare i propri prodotti, Karma Italiana si riserva il diritto di apportare modifiche ai propri prodotti senza alcun preavviso. Tutti i prodotti Karma sono conformi alle normative vigenti dell'Unione Europea.