



PRODUCT TECHNICAL SHEET

30 June 2024

PA 2362BT

2 x 30W stereo amplifier

This compact stereo amplifier is ideal for use in shops, receptions or homes. Thanks to the back sockets it is possible to connect 2 x 30W speakers. The input signals can be mixed by means of the volume controls on the front panel and the entire mixing tone can be adjusted at will. The multimedia module offers the possibility to play songs from SD, USB or via bluetooth.

It features 3 inputs: 2 for the connection of two microphones (via the 6.3mm mono jack on the front side) and 1 line input for external sources (such as CD players, decoders, etc.) through the RCA sockets on the back. The front panel is also equipped with SD and USB sockets with keys to play MP3 tracks. It also comes with bluetooth function to play audio from a smartphone or tablet, echo effect, balancing and bass & treble adjustment.

It includes also FM radio and remote control.



RMS power	2 x 16W (4 Ohm)
SD player	Yes, included
Distortion	0,1%
Input signal level	200 mV
S/N ratio	75dB
2 Ohm supported	No
Max power	2 x 30W
Bridge function	No
Bluetooth	Ver. 5.0
Radio	Yes, FM
Remote control	Included
Frequency response	20Hz - 20kHz
Display	Yes
Output connectors	clip
Input connectors	RCA + 6,3mm Jack
8 Ohm max power	2 x 16W
4 Ohm max power	2 x 30W
Color	Black
Weight	1,6 kg
Product dimensions	180 x 70 x 165 mm
Power supply	220V - 12V

Puoi trovare articoli correlati, accessori ed aggiornamenti su:

www.karmaitaliana.it

Inoltre potrai scaricare i nostri cataloghi in formato PDF per:

- DeeJay - Mixer & Disco Light - Microfoni e raddiomicrofoni - Alimentatori / accessori - Staffe porta TV - Amplificazione stereo - Diffusori passivi / amplificati - Sicurezza



8015439923815