



PRODUCT TECHNICAL SHEET

30 June 2024

CVS 908

Audio signal converter

Audio signal converter. It can transform a microphone or phono type signal into a "line" signal. For example, if you need to connect a microphone to a stereo amplifier lacking the specific connector, you can use this fixture avoiding to buy a mixer.

Input Impedance: 50K ohms - 1kHz
Input level: 0.5 mV, MIC - 3mV PHONO
Gain: 50dB MIC - 34dB PHONO
Signal to noise ratio:> 48dB MIC -> 55dB PHONO
Frequency Response. (MIC): +1 db-bdb 70Hz - 20kHz
Equalizer (PHONO): RIAA +1 db to-3db 30Hz - 20kHz
Output Level: 150mV RMS
Load Impedance:> 10K ohms
Overload margin: 23dB / Crosstalk: 55dB
Power supply: 12-15V DC 100mA - Polo + Central

Input connectors	RCA + 6,3mm Jack
Output connectors	RCA
Frequency response	70Hz - 20KHz
Weight	0.25
Product dimensions	135 x 70 x 40 mm
Color	Black
Power supply	12V DC through adaptor
Notes	Power adaptor included



Puoi trovare articoli correlati, accessori ed aggiornamenti su:

www.karmaitaliana.it

Inoltre potrai scaricare i nostri cataloghi in formato PDF per:

- DeeJay - Mixer & Disco Light - Microfoni e raddiomicrofoni - Alimentatori / accessori - Staffe porta TV - Amplificazione stereo - Diffusori passivi / amplificati - Sicurezza



8015439209087