



PRODUCT TECHNICAL SHEET

30 June 2024

MXP 08

8-channel microphone mixer

8-channel microphone mixer for professional appliance thanks to its many functions. It allows connection of 4 balanced microphones and up to 8 line signals. Each channel is endowed with independent tone control. A particular DSP offers 16 preset reverb effects. The MP3 module can reproduce tracks from USB keys. The same USB socket can be used for connection to PCs or to send or receive audio signals (cable included). It also comes with bluetooth receiver.

Input connectors	XLR + RCA + Jack 6,3mm
Output connectors	XLR + 6,3mm Jack
Line inputs	8
Mic inputs	4
Number of channels	8
Effects	DSP 16bits
Phantom Key	Yes, it allows to enable phantom power for condenser microphones
VU METERS	Yes
Frequency response	20 Hz - 20 KHz
Color	black
Weight	1.7
Product dimensions	371 x 258 x 80 mm
Power supply	110V - 220V



+48V PHANTOM **4 MIC** **8 CANALI** **8 LINEA** **DSP FUNCTION** **MP3 PLAYER** **USB**



Puoi trovare articoli correlati, accessori ed aggiornamenti su:

www.karmaitaliana.it

Inoltre potrai scaricare i nostri cataloghi in formato PDF per:

- DeeJay - Mixer & Disco Light - Microfoni e raddiomicrofoni - Alimentatori / accessori - Staffe porta TV - Amplificazione stereo - Diffusori passivi / amplificati - Sicurezza



8015439260088