



PRODUCT TECHNICAL SHEET

30 June 2024

SET 8202PL

Dual UHF wireless microphone with handmic and headset

Wireless microphone with handmic and headset operating in UHF band. Both the microphones and the receiving base are endowed with display for the operating frequency control and battery charge level.

The receiving base is powered by an ordinary USB socket (cable and power adaptor included). Thanks to this peculiarity it can be connected to amplified speakers, mixers, power banks, notebooks or any device endowed with USB socket. Another exclusive feature is the possibility to change the operating frequency (16 channels available) directly from the microphone, rather than from the base. Thanks to the practical XLR and Jack 6,3 mm sockets it is possible to obtain an easy and professional connection.



Autonomy	Min 8 hours
Output connectors	XLR + 6,3mm Jack
Display	Yes
Diversity system	No
Frequency type	UHF
Operating range	50m
Receiver dimensions	175 x 40 x 120 mm
Frequency response	30Hz - 20 KHz
Carrying case	No
Color	black
Weight	1,3
Product dimensions	175 x 40 x 120 mm 175 x 40 x 120 mm
Power supply	Through USB
Notes	Frequency range: CH 1 679.100 - 694.100 - CH 2 663.100 - 678.100 Mhz

Puoi trovare articoli correlati, accessori ed aggiornamenti su:

www.karmaitaliana.it

Inoltre potrai scaricare i nostri cataloghi in formato PDF per:

- DeeJay - Mixer & Disco Light - Microfoni e raddiomicrofoni - Alimentatori / accessori - Staffe porta TV - Amplificazione stereo - Diffusori passivi / amplificati - Sicurezza



8015439382025