

# KARMA®

— GLEMM — rídem —

SCHEDA TECNICA / TECHNICAL SHEET

## PAA 50T

50W amplifier



DOWNLOAD 

Scarica ora  
il catalogo aggiornato



SCOPRI TUTTE LE NOVITÀ  
SUL NOSTRO SITO

[www.karmaitaliana.it](http://www.karmaitaliana.it)



8015439110505

Versatile and compact at the same time (only 32,5 cm). It can be powered both by 220V mains power and by 12V-24V battery. It is possible to control 2 microphones, 1 line signal and 1 phone signal (for turntables) and to connect speakers for 4-8 Ohm as well as 70/100V operation. It includes a MP3 player, a bluetooth receiver and a practical FM radio receiver. The inputs' volume can be adjusted independently. It is possible to modify high and low output tones. Priority on the main microphone. Remote control included.

MP3 compatible	Yes
Input connectors	RCA + 6,3mm Jack
Output connectors	Terminals
Line inputs	1
Mic inputs	2
Impedance	4 - 8 Ohms
Constant voltage	70 - 100V compatible
Multi zone	No
8 Ohm max power	50W
Frequency response	100Hz - 20 KHz
Voice priority function	Yes
VU METERS	No
Phantom Key	No
RMS power	30W
Matrix	No
Max power	50
DC Power	12V - 24V
Bluetooth	Ver. 5.0
Color	black
Weight	4,2
Product dimensions	325 x 85 x 220mm
Power supply	AC 220V, DC 12-24V
Notes	Remote control included

Karma Italiana srl si impegna affinché le informazioni contenute in questa scheda siano le più precise possibili. Allo scopo di migliorare i propri prodotti, Karma Italiana si riserva il diritto di apportare modifiche ai propri prodotti senza alcun preavviso. Tutti i prodotti Karma sono conformi alle normative vigenti dell'Unione Europea.