

KARMA®

— GLEMM — rídem —

SCHEDA TECNICA / TECHNICAL SHEET

PAA 240MZ

240W 6 zone amplifier



Complete and performant PA amplifier. It can manage up to 240W of power distributed over 6 zones, each of them with independent volume control. It is possible to connect up to 6 input signals (1 mic + 3 line/mic + 2 line). Three of the four mic inputs support phantom power supply. The volume controls on the front panel are quick and practical to use. Thanks to a sophisticated multimedia module it is possible to play Mp3 tracks (via SD or USB), listen to radio stations and connect to bluetooth devices.

Input connectors	XLR + jack 6,3mm
Output connectors	Terminals
Rack space	2U
Line inputs	6 (1 mic + 3 line/mic + 2 line)
Mic inputs	4 (3 x XLR with phantom + 1 x 6,3mm jack)
Impedance	4 - 8 - 16 Ohms
Constant voltage	70 - 100V compatible
Multi zone	6 zones, each with independent volume
Frequency response	80Hz - 16KHz
VU METERS	Yes
Phantom Key	Yes
RMS power	120W
Mp3 player	Yes
Matrix	No
Max power	240W
DC Power	24V
Bluetooth	Ver. 5.0
Color	black
Weight	9,5 kg
Product dimensions	484 x 88 x 405mm
Power supply	220V

DOWNLOAD 

Scarica ora
il catalogo aggiornato



SCOPRI TUTTE LE NOVITÀ
SUL NOSTRO SITO

www.karmaitaliana.it



8015439132408

Karma Italiana srl si impegna affinché le informazioni contenute in questa scheda siano le più precise possibili. Allo scopo di migliorare i propri prodotti, Karma Italiana si riserva il diritto di apportare modifiche ai propri prodotti senza alcun preavviso. Tutti i prodotti Karma sono conformi alle normative vigenti dell'Unione Europea.