



PRODUCT TECHNICAL SHEET

30 June 2024

PAA 1000MZ

1000W 6 zone amplifier

Complete and performant PA amplifier. It can manage up to 1000W of power distributed over 6 zones, each of them with independent volume control. It is possible to connect up to 6 input signals (1 mic + 3 line/mic + 2 line). Three of the four mic inputs support phantom power supply.

The volume controls on the front panel are quick and practical to use. Thanks to a sophisticated multimedia module it is possible to play Mp3 tracks (via SD or USB), listen to radio stations and connect to bluetooth devices.

MP3 compatible	Yes
Input connectors	XLR + jack 6,3mm
Output connectors	Terminals
Rack space	2U
Line inputs	6 (1 mic + 3 line/mic + 2 line)
Mic inputs	4 (3 x XLR with phantom + 1 x 6,3mm jack)
CD/ USB	USB and SD
Impedance	4 - 8 - 16 Ohms
Constant voltage	70 - 100V compatible
Multi zone	6 zones, each with independent volume
Phantom Key	Yes
RMS power	500W
Mp3 player	Yes
Matrix	No
Max power	1000w
DC Power	24V
Bluetooth	Ver. 5.0
Color	black
Weight	11
Product dimensions	484 x 88 x 405
Power supply	220V



Puoi trovare articoli correlati, accessori ed aggiornamenti su:

www.karmaitaliana.it

Inoltre potrai scaricare i nostri cataloghi in formato PDF per:

- DeeJay - Mixer & Disco Light - Microfoni e raddiomicrofoni - Alimentatori / accessori - Staffe porta TV - Amplificazione stereo - Diffusori passivi / amplificati - Sicurezza



8015439881009