



PRODUCT TECHNICAL SHEET

30 June 2024

MMX 11

11 input mixer pre-amplifier

Rack fixture useful both as 11 input mixer and as stereo preamplifier. It is possible to connect to the back panel up to 6 microphones (with + 48V phantom power supply) through XLR and 5 signals through RCA connectors. It is endowed with stereo output both through RCA and XLR. It can operate also powered by an external 24V battery. Priority function.

| | |
|-------------------------|--------------------|
| Pre-listening | No |
| Rack space | 1U |
| VU METERS | Yes |
| Number of channels | 6 |
| Mic inputs | 6 |
| Line inputs | 4 + 1 EMC |
| Output connectors | XLR + RCA |
| Input connectors | XLR + RCA |
| S/N ratio | >70dB |
| Frequency response | 60 Hz - 15 KHz |
| Voice priority function | Yes, on MIC 1 only |
| Color | black |
| Weight | 1.4 |
| Product dimensions | 483 x 440 x 100 mm |
| Power supply | 220V - 24V |



Puoi trovare articoli correlati, accessori ed aggiornamenti su:

www.karmaitaliana.it

Inoltre potrai scaricare i nostri cataloghi in formato PDF per:

- DeeJay - Mixer & Disco Light - Microfoni e raddiomicrofoni - Alimentatori / accessori - Staffe porta TV - Amplificazione stereo - Diffusori passivi / amplificati - Sicurezza



8015439900113