



## PRODUCT TECHNICAL SHEET

30 June 2024

### PAA 120M2Z

#### 120W 2-zone amplifier

PA amplifier suitable for 70/100V or low impedance operation. 100V signals can also be managed thanks to its 2 zones. It is possible to connect up to 3 microphones and 4 line signals, each with independent volume control. Phantom power and priority function can be activated on microphone 1. It is equipped with terminals for a monitor speaker and sockets for 24V power supply. The multimedia module can play MP3 songs from microSD, USB, bluetooth. It is also endowed with FM radio. The maximum power is 120W.



MP3 compatible	Yes
Input connectors	XLR + RCA + Jack 6,3mm
Output connectors	terminals + RCA
Line inputs	4
Mic inputs	3
Impedance	4 - 8 - 16 Ohms
Constant voltage	70 - 100V compatible
Multi zone	2 zones
S/N ratio	Line >85dB, Mic > 72dB
Frequency response	60 Hz - 15 KHz (+/-3dB)
Voice priority function	Yes, on MIC 1 only
VU METERS	Yes
Phantom Key	Yes
RMS power	60
Multizone	2 zones
Mp3 player	Yes
Tel paging function	Yes
Matrix	No
Max power	120
DC Power	24V
Bluetooth	yes
Color	Black
Weight	4,2 kg
Product dimensions	320 x 210 x 90 mm
Power supply	220V - 24V

Puoi trovare articoli correlati, accessori ed aggiornamenti su:

[www.karmaitaliana.it](http://www.karmaitaliana.it)

Inoltre potrai scaricare i nostri cataloghi in formato PDF per:

- DeeJay - Mixer & Disco Light - Microfoni e raddiomicrofoni - Alimentatori / accessori - Staffe porta TV - Amplificazione stereo - Diffusori passivi / amplificati - Sicurezza



8015439241209