

PAA 2480

960W 2-zone amplifier



Professional PA amplifier suitable both for 100V and 8 Ohm signals. It comes with 2 matrix zones to manage 4 line signals and 3 microphone signals. Thanks to its multimedia module it can play MP3 audio from USB sticks, TF cards and bluetooth connections. It includes a sophisticated latest generation FM and DAB+ radio receiver. It also features alarm signal, siren effect and mute function. Each input is independently adjustable in treble and bass. The maximum power is 480W per zone.

| MP3 compatible | Yes |
|-------------------------|-------------------------------------|
| Input connectors | XLR + RCA |
| Output connectors | Terminals |
| Rack space | 2U |
| Line inputs | 4 |
| Mic inputs | 3 |
| CD/ USB | It includes USB module with display |
| Input impedance | 8-16 Ohm |
| Siren & Whistle | Siren |
| Constant voltage | 100V compatible |
| Multi zone | 2 zones |
| 8 Ohm max power | 960W |
| S/N ratio | Line >85dB, Mic > 72dB |
| Frequency response | 60 Hz - 15 Khz (+/-3dB) |
| Voice priority function | No |
| RMS power | 480W |
| Multizone | 2 zones |
| Mp2 mayer | Yes |
| e orging function | No |
| Matrix | Yes |
| Max power | 960 |
| Bluetooth | yes |
| Color | black |
| Weight | 9,6 kg |
| Product dimensions | 484 x 405 x 88 mm |
| Power supply | 110V - 230V |



SCOPRI TUTTE LE NOVITÀ SUL NOSTRO SITO (1)

www.karmaitaliana.it



Karma Italiana srl si impegna affinchè le informazioni contenute in questa scheda siano le più precise possibili. Allo scopo di migliorare i propri prodotti, Karma Italiana si riserva il diritto di apportare modifiche ai propri prodotti senza alcun preavviso. Tutti i prodotti Karma sono conformi alle normative vigenti dell'Unione Europea.