

KARMA®

— GLEMM — rídem —

SCHEDA TECNICA / TECHNICAL SHEET

PAA 130

130W D class mini amplifier



DOWNLOAD 

Scarica ora
il catalogo aggiornato



SCOPRI TUTTE LE NOVITÀ
SUL NOSTRO SITO

www.karmaitaliana.it



8015439401306

Small amplifier, easy to use and very solid. It can be connected to low impedance or constant voltage speakers and features microphone and line signal inputs. It can deliver a maximum power of 130W. It can be also powered at 24V (useful for trucks and buses). The Mp3 module can play audio from USB devices or via bluetooth.

| | |
|--------------------|------------------------|
| MP3 compatible | Yes |
| Input connectors | RCA + 6,3mm Jack |
| Output connectors | Terminals |
| Line inputs | 1 |
| Mic inputs | 1 |
| Input impedance | 4 - 8 - 16 Ohm |
| Constant voltage | 100V compatible |
| 8 Ohm max power | 130W |
| Frequency response | 80Hz - 18KHz (+/- 3dB) |
| Phantom Key | No |
| RMS power | 60W |
| Multizone | no |
| Mp3 player | Yes |
| Matrix | No |
| Max power | 130 |
| DC Power | 24V |
| Bluetooth | yes |
| Color | black |
| Weight | 2,3 kg |
| Product dimensions | 280 x 180 x 65mm |
| Power supply | 110V - 230V |

Karma Italiana srl si impegna affinché le informazioni contenute in questa scheda siano le più precise possibili. Allo scopo di migliorare i propri prodotti, Karma Italiana si riserva il diritto di apportare modifiche ai propri prodotti senza alcun preavviso. Tutti i prodotti Karma sono conformi alle normative vigenti dell'Unione Europea.