



PRODUCT TECHNICAL SHEET

30 June 2024

SET 8302LAV

Dual UHF wireless microphone with headset

Compact and efficient wireless microphone with two headset transmitters. It features 48 channels to operate in any condition. It covers a range of 50m with very good audio performance both for speech and for song. The receiver base features both a balanced XLR socket and a 6,3mm mixed socket. It can be powered from an ordinary USB socket and comes with a wide display showing all main information. Thanks to the easy change system it is possible to change the channel directly from the microphone. The transmitter is powered by 2 AA batteries (not included).

Output connectors	XLR + 6,3mm Jack
Frequency type	UHF
Display	Yes
Operating range	50m
Receiver dimensions	210 x 40 x 180mm
Headband weight	0,070 kg
Frequency response	30Hz - 20KHz
Sensitivity	-96dbm
Carrying case	Included
Color	Black
Weight	0,388
Power supply	5V DC (via power adaptor)
Notes	Frequency A: 679.100 MHz - 693.400 MHz Frequency B: 663.100 MHz - 677.400 MHz



Puoi trovare articoli correlati, accessori ed aggiornamenti su:

www.karmaitaliana.it

Inoltre potrai scaricare i nostri cataloghi in formato PDF per:

- DeeJay - Mixer & Disco Light - Microfoni e raddiomicrofoni - Alimentatori / accessori - Staffe porta TV - Amplificazione stereo - Diffusori passivi / amplificati - Sicurezza



8015439383022